



## 2-Channel Professional UHF Receiver - URX2

### FEATURES

- § 2 Channels
- § Walkman Style Headphones
- § Signal received LED
- § DC Power socket for mains or car supply
- § Separate fixed level record out socket for connection to suitable recorders (lead supplied)
- § High gain flexible nickel-titanium quarter-wave antenna
- § Protective plastic case for receiver and accessories included

The URX-2 is a dedicated pocket sized, 2-channel receiver for monitoring our range of UHF Room and Telephone Transmitters. Simply switch the receiver on, select the relevant channel and listen with amazing clarity through walkman style headphones. A separate record output socket allows any compatible tape or digital recorder to be connected without the need for level adjustment.

### Optional Accessories

- § Mains Power Adapter
- § Car Cigarette lighter Adaptor
- § Miniature 5cm 'stub' antenna
- § Magnetic mount high gain vehicle antenna



### TECHNICAL SPECIFICATIONS

Typical Performance Characteristics - at 20 degrees C

<b>Dimensions:</b>	82mm x 58mm x 22 mm
<b>Power Supply:</b>	Battery 9 Volt PP3 alkaline DC socket 9V 200 mA regulated
<b>Antenna connector:</b>	MCX 50 Ohm
<b>Headphone output:</b>	3.5mm stereo jack socket – 1 Watt max into 8 Ohms
<b>Record output:</b>	3.5 mm mono jack socket – microphone level
<b>Receiver sensitivity:</b>	0.22uV +/- 10% dB SINAD
<b>Frequency accuracy:</b>	Better than 0.0005% or receive frequency
<b>Frequency control:</b>	Independent quartz crystal
<b>Modulation:</b>	Narrow Band FM 3 KHz bandwidth
<b>Current consumption:</b>	Standby – 23 mA Receive (no phones) – 40mA Receive (with phones) – 60 mA nominal
<b>Operating Temperature:</b>	-10 to +60 C